

impact protection.

The 88V is independently tested to comply with the 2nd edition of ANSI/ISA S82.01 and EN61010-1 CAT IV 600 V/CAT III 1000 V. They can withstand impulses in excess of 8,000 V and reduce risks related to surges and spikes.

Other useful features:

- Lifetime warranty
- 6000 counts, 3-3/4 digits
- Measure up to 1000 V AC and DC
- Measure up to 10 A, 20 A for up to 30 seconds
- Built in thermometer lets you carry one less tool (temperature probe included)
- Frequency to 200 kHz and % duty cycle
- Resistance, continuity
- RPM measurements with inductive pickup
- Millisecond pulse width measurements for fuel injectors
- Magnet hanger to attach meter to the vehicle and free your hands for other tasks
- 10,000 μ F capacitance range for components and motor caps
- Min/Max-Average recording with Min/Max Alert to capture variations automatically
- Peak capture to record transients as fast as 250 μ s
- Relative mode to remove test lead interference from low ohms measurements
- Auto and manual ranging for maximum flexibility
- Touch Hold to capture stable readings avoiding noisy signals
- Large display digits and two-level bright white backlight for increased visibility
- Analog bargraph for fast changing or unstable signals
- Input Alert provides audible warning against wrong use of input jacks
- Improved selectable sleep mode for long battery life
- Access door for fast battery changes without opening up the case
- "Classic" design with new removable holster with built in test lead and probe storage
- 10 meg ohm input impedance wont load circuits
- 0.1% DC accuracy

Position the meter in the most usable location with the magnetic hanger

The holster on the new Fluke 88V accepts a small but extremely powerful magnet (Fluke Tpak) that holds the meter firmly to most steel surfaces. This allows you to focus on taking measurements instead of holding the meter in your hand.

Electrical safety

All inputs are protected to Category III, 1000 V and Category IV 600 V. They can withstand impulses in excess of 8,000 V and reduce risks related to surges

Specifications: Automotive Multimeters: Fluke 88V/A Automotive

Multimeter Combo Kit

Technical Specifications		
DCV	Maximum Voltage	1000 V
	Accuracy	$\pm(0.1\% + 1)$
	Best Resolution	0.01 mV
ACV	Maximum Voltage	1000 V
	Accuracy	$\pm(0.5\% + 2)$
	AC Bandwidth	5 kHz
	Best Resolution	0.01 mV
DC Current	Maximum Amps	10 A
	Amps Accuracy	$\pm(0.4\% + 2)$
	Best Resolution	0.001 mA
AC Current	Maximum Amps	10 A
	Amps Accuracy	$\pm(1.2\% + 2)$
	Best Resolution	0.001 mA
Resistance	Maximum Resistance	50 M Ω
	Accuracy	$\pm(0.4\% + 1)$
	Best Resolution	0.1 Ω
Capacitance	Maximum Capacitance	9,999 μ F
	Accuracy	$\pm(1\% + 2)$
	Best Resolution	0.01 nF
Frequency	Maximum Frequency	200 KHz
	Accuracy	$\pm(0.005\% + 1)$
	Best Resolution	0.01 Hz
Duty Cycle	Maximum Duty Cycle	99.9%
	Accuracy	within 2% per KHz +0.1%
	Best Resolution	0.1%
Temperature Measurement	-200.0°C - 1090°C -328.0°F - 1994.0°F, 1.0% excluding probe	
80 BK Temperature Probe	-40°C - 260°C -40°F - 500°F, 2.2°C or 2% whichever is greater	
Conductance	Maximum Conductance	60.00 nS
	Accuracy	$\pm(1.0\% + 10)$
	Maximum Resolution	0.01 nS



Operating Range	Operating Temperature	-20°C - 55°C
	Storage Temperature	-40°C - 60°C
Physical	5.2 x 9.8 x 20.1 cm (2.06 x 3.86 x 7.93 in) 624 g (22 oz)	

Ordering information



Fluke 88V/A Kit

Fluke 88V/A Automotive Multimeter Combo Kit

Includes:

- 88V Automotive Multimeter
- TL224 silicone test leads
- AC285 long reach alligator clips
- TP220 test probes
- RPM 80 inductive RPM
- TPAK ToolPak™ Magnetic Meter Hanging Kit
- 80BK temperature probe
- Two automotive backprobe pins
- Insulation piercing probe
- C800 durable carrying case
- Holster
- 9V battery (installed)
- Getting started manual
- CD with detailed manual

Fluke. *Keeping your world up and running.®*

Fluke Europe B.V.

P.O. Box 1186
5602 BD Eindhoven
The Netherlands
www.fluke.com/en

©2021 Fluke Corporation. All rights reserved.

Data subject to alteration without notice.

12/2021

For more information call:

In Middle East/Africa
+31 (0)40 267 5100

**Modification of this document is not permitted
without written permission from Fluke Corporation.**